

1. Application

JR-SS electronic overload relay is suitable for AC 50/60Hz, voltage up to 600VAC and current up to 60A. It is used as overload and phase loss protection, independently adjustable starting and trip delay, visual current setting aid and trip indication, fail safe protection (N type) and electronic shear pin function. The product conforms to IEC60947-1 standard.

2. Specification



Type	JR-SS		
Current range	05)0.5-5A(scale 6.5A)		
	30)3-30A(scale 35A)		
	60)5-60A(scale 70A)		
Rated voltage	600VAC,50/60Hz		
Operation setting	D-TIME	0.2-30seconds	
	O-TIME	0.2-10seconds	
Accuracy	Current	±10%	
	Time	±15% of max.time set value	
Time characteristics	Definite time		
Control voltage	220)Voltage free(90~260)VAC,50/60Hz 440)Voltage free(320~480)VAC,50/60Hz Other voltage optional.		
Current sensing	2 CTs		
Output contacts	Contacts		SPDT 3A/250VAC Resistive
	Condition	N Type	Normally energized:95- -98closed
		R Type	Normally De-energized:95- / -98closed
Reset	Manual or remote electrical by interrupting supply		
Environment	Temp. Run	Run	-20+70 deg.°C
		Store	-30+80 deg.°C
	Humidity		45~85% RH,non-condsing
Insulation	Between casing and circuits:Over 10MΩ with DC 500V megger		
Dielectric strength	1)Between casing & circuits:AC 2000V,60Hz,1 min		
	2)Between contacts:AC 1000V,60Hz,1 min		
	3)Between contacts:AC 2000V,60Hz,1 min		
Power consumption	Under 2W		
Mounting	35mm Din Rail(D)		
The run-up current of motor(starting current)does relay trip because overcurrent protection of AJR-SS is not applied during motor run-up time.			

The run-up current of motor(starting current)does relay trip because overcurrent protection of AJR-SS is not applied during motor run-up time.