

1. Application

CJX2-K series AC contactor is suitable for use in the circuit up to the rate and frequent starting, controlling the AC motor. The addition of auxiliary contact group to the contactor, combined with the proper thermal relay, can act to protect the circuit bound to overload. It conforms to IEC60947-4-1.

2. Specification



Type			CJX2-K06	CJX2-K09	CJX2-K12
Rating working voltage(V)	380V	AC-3	6	9	12
		AC-4	2.6	3.5	5
Appointed heating current(A)			16	20	20
The max current when turn on(A)		380V	60	90	120
		660V	72	108	144
The max current for turn off(A)		380V	48	72	96
		660V	60	90	120
Three phases cage motors power whichcan be pulled AC3(KW)		220v	1.5	2.2	3
		380v	2.2	4	5.5
		660v	3	4	4
Operation frequency(time/hour)	Electricity life(x10 ⁴)	AC-3	1200		
		AC-4	300		
Electrical life	AC-3		5x10 ⁶		
	AC-4		1x10 ⁵		
Mechanical life			3x10 ⁶		

3. Outline and Mounting Dimension


