

1. Application

BYX-JZ series signal surge protect device is mainly used to protect telephone and fax machine line, DDN and ISDN special line, computer connect port and auto control equipment. Mounting: 35mm DIN rail in series Way: 1,4,8,12,16,24



Type	BYX-JZ GC110	BYX-JZ GD110	BYX-JZ GC48	BYX-JZ GD48	BYX-JZ GC24	BYX-JZ GD24	BYX-JZ GF48	BYX-JZ GF24
Rated voltage Un	DC110V		DC48V		DC24V		DC48V	DC24V
Maximum continuous operating voltage Uc	DC150V		DC60V		DC30V		DC60V	DC30V
Limiting voltage Up (10/700 uS)	≤500V		≤200V		≤120V		≤200V	≤120V
Nominal discharge current (8/20uS) In (KA)	10KV							
Surge protected volage Ur (1kV/uS)	≤600V							
Transmission Frequency	2MHz	10MHz	2MHz	10MHz	2MHz	10MHz	100MHz	
Insertion loss	<0.5db						≤3db	
Connect model	Terminals							
Protect cores	1,2							
Protect method	Whole protection mode							
Response time T	<10ns							